



PANOS 2.25" & 3.50" Pendant Surface Mount D00609CI

WHEN REPLACING PCB ASSEMBLIES, PLEASE WEAR AN ESD WRIST STRAP AND CONNECT IT TO ELECTRICAL GROUND

RISK OF FIRE AND ELECTRICAL SHOCK

Contact, improper installation, or improper servicing MAY RESULT IN DEATH OR SERIOUS INJURY! Fixture must be installed by a qualified electrician only. Fixture is intended for installation in accordance with the National Electrical Code, local and federal code specifications. Disconnect power at electrical panel before servicing. Retain these instructions for maintenance reference.

ADVERTENCIA: RIESGO DE INCENDIO O IMPACTO ELÉCTRICO

Conexión, instalación inapropiada o servicio incorrecto PUEDE CAUSAR MUERTE O HERIDAS GRAVES. La luminaria debe ser instalada únicamente por un eléctrico calificado. La luminaria debe instalarse de acuerdo al Norma eléctrica nacional, al igual que especificaciones locales y normas federales. Se debe desconectar la corriente eléctrica antes de realizar la mantención. Conservar estas instrucciones como referencia para futuras mantenciones.


ATTENTION: RISQUE D'INCENDIE ET D'ELECTROCUTION

Une installation, un entretien ou un contact physique non conforme pourraient mener à un DANGER DE MORT OU DE BLESSURE GRAVE! L'appareil doit être installé uniquement par un électricien professionnel qualifié. L'installation doit respecter le code électrique national de même que les lois locales et fédérales en vigueur. Veuillez fermer l'alimentation électrique au panneau principal avant tout entretien. Conserver ces instructions pour référence et tout entretien futur.


NOTE

National or municipal codes must be followed regarding fixture installation and set back of thermal insulating material from luminaire. As a guideline, any insulation material must be held away from the luminaire by minimum of 3". Fixtures are not designed for direct contact with thermal insulation.


The following installation instructions relate to the options below




**2.25" PANOS Pendant
Surface Mount**



**3.50" PANOS Pendant
Surface Mount**




**2.25" PANOS Pendant
Square Surface Mount**






**3.50" PANOS Pendant
Square Surface Mount**

1 Surface Mount




2 Round




i

a




2.25"/3.50"
(68mm/100mm)

Round



2.25"
(68mm)


Square



3.50"
(100mm)

Square

For Standard Config



18Ga Pigtail


Color Codes

Black	Switched Hot
White	Neutral
Green	Ground
Red	Unswitched Hot
Violet	Control +
Pink	Control -

May not be present depending on driver options


For Tunable White Options

b




2.25"/3.50"
(68mm/100mm)

Round



2.25"
(68mm)

Square



3.50"
(100mm)

Square


Color Codes

Black	Switched Hot
White	Neutral
Green	Ground
Red	Unswitched Hot
Violet	Intensity +
Pink	Intensity -
Violet	Color Temp +
Pink	Color Temp -


May not be present depending on driver options

3

Round - Mount




Square - Mount




4

Round - Removal

Push up a little distance, then rotate




Square - Removal



3 For Asymmetric Lens Adjustment - Round Only

Available in 3.5" (100mm) round only




Use suction cup provided to move lens in direction required-COB should appear to be opposite direction of the light

Warning:

* Do not rotate fixture body while adjusting lens, to avoid fixture unlocking

For Wall Wash Lens - Square Only

Available in 3.5" (100mm) square only



Be sure to orient fixture as seen above to get desired, wall wash effect